

The monitor types will have to be changed as well, as the properties of the class are not passed through in the template version of the monitor.

Updated Code:

```
<UnitMonitorType ID="TCPPortMonitor.TimeOut.MonitorType" Accessibility="Public">
  <MonitorTypeStates>
    <MonitorTypeState ID="TimeOutFailure" NoDetection="false" />
    <MonitorTypeState ID="NoTimeOutFailure" NoDetection="false" />
  </MonitorTypeStates>
  <Configuration>
    <xsd:element name="ServerName" type="xsd:string" />
    <xsd:element name="Port" type="xsd:int" />
    <xsd:element name="NoOfRetries" type="xsd:int" />
    <xsd:element name="TimeWindowInSeconds" type="xsd:int" />
  </Configuration>
  <MonitorImplementation>
    <MemberModules>
      <DataSource ID="DS1" TypeID="TCPPortMonitor.TCPPortCheck.DataSource">
        <ServerName>$Config/ServerName$</ServerName>
        <Port>$Config/Port$</Port>
        <NoOfRetries>$Config/NoOfRetries$</NoOfRetries>
        <TimeWindowInSeconds>$Config/TimeWindowInSeconds$</TimeWindowInSe
conds>
      </DataSource>
      <ConditionDetection ID="CDTimeOutFailure"
TypeID="System!System.ExpressionFilter">
        <Expression>
          <SimpleExpression>
            <ValueExpression>
              <XPathQuery Type="UnsignedInteger">StatusCode</XPathQuery>
            </ValueExpression>
            <Operator>Equal</Operator>
            <ValueExpression>
              <Value Type="UnsignedInteger">2147952460</Value>
            </ValueExpression>
          </SimpleExpression>
        </Expression>
      </ConditionDetection>
      <ConditionDetection ID="CDNoTimeOutFailure"
TypeID="System!System.ExpressionFilter">
        <Expression>
          <SimpleExpression>
            <ValueExpression>
              <XPathQuery Type="UnsignedInteger">StatusCode</XPathQuery>
```

```
</ValueExpression>
<Operator>NotEqual</Operator>
<ValueExpression>
<Value Type="UnsignedInteger">2147952460</Value>
</ValueExpression>
</SimpleExpression>
</Expression>
</ConditionDetection>
</MemberModules>
<RegularDetections>
<RegularDetection MonitorTypeStateID="TimeOutFailure">
<Node ID="CDTimeOutFailure">
<Node ID="DS1" />
</Node>
</RegularDetection>
<RegularDetection MonitorTypeStateID="NoTimeOutFailure">
<Node ID="CDNoTimeOutFailure">
<Node ID="DS1" />
</Node>
</RegularDetection>
</RegularDetections>
</MonitorImplementation>
</UnitMonitorType>
```